



### FHM2 Series Optical Multimeter

- Integrated laser source and optical power meter
- Dual or triple wavelength output
- Suitable for fiber or device insertion loss test
- Up to 999 test results storage
- With LCD backlight function and auto power off

Model	Specifications			
	FHM2A01	FHM2A02	FHM2B01	FHM2B02
<b>Laser Source Part (LD)</b>				
Output Wavelength	1310/1550nm	1310/1490/1550nm	1310/1550nm	1310/1490/1550nm
Output Power	-5dBm±0.5dB	0dBm±0.5dB	-5dBm±0.5dB	0dBm±0.5dB
Frequency Output	270Hz/1kHz/2kHz			
Wavelength Recognition	1310/1550nm	1310/1490/1550nm	1310/1550nm	1310/1490/1550nm
<b>Power Meter Part (PD)</b>				
Test Range	-70~+10dBm		-50~+26dBm	
Resolution	0.01dB			
Calibrated Wavelength	850/1300/1310/1490/1550/1625nm			
Accuracy	±0.2dB			
Frequency Detection	270Hz/1kHz/2kHz			
Wavelength Detection	Support			
Memory Capacity	999 groups			
<b>Others</b>				
Communication Port	USB			
Power Supply	2* Ni-MH AA battery			
Working Temp	-10°C~+50°C			
Storage Temp	-20°C~+70°C			
Dimension/Weight	160L×76W×45H(mm) / 260g			
Accessories	(LD)FC&SC adapter, (PD)FC&SC adapter, 2*Ni-MH AA battery, 3*ceramic sleeves, Power adapter, USB cable, CD, Test report, Quick guide, Carrying bag			
Optional	(PD) 1.25mm adapter/2.5mm adapter			

Let's go in me grandway!